

### Follow These Instructions As They Are In Order

- First you would want to go to our website.
  - [www.eGPS.net](http://www.eGPS.net)
  - Please find the SUPPORT selection, then choose “Guides, Software, & Firmware”.
- Select the PRO GNSS Receiver tab
  - Please find Updating Your Pro
    - You will need to download the following files:
      - **Note: These Files Are For The Pro GNSS Receiver Only**
      - Updating Your PRO | PDF
      - Config-1.6.55\_20Hz | CFG
      - radio\_channel\_Champion | CFG
      - update\_gnss\_v5.42\_02\_b20190812 | BIN
      - update\_Pro\_v1.6.55\_20Hz\_b20181201 | BIN
- Turn on Champion Pro GPS Unit
- Connect
  - Select internet access from your toolbar
  - GPS unit will show up as GNSS-(Serial number)
    - Password is 12345678
- GPS IP address
  - <http://192.168.1.1>
    - If you can't see this webpage, you are not connected.
  - Login
    - User: admin
    - Password: password
  - Choose firmware on the bottom-left of the page
    - Choose Firmware Update
      - Click Browse
      - You will use file update\_Pro\_v1.6.55\_20Hz\_b20181201
- Connect to GPS unit again
- Radio Channel Configuration
  - Radio IP Address
    - [http://192.168.1.1/set\\_en.html](http://192.168.1.1/set_en.html)
      - Click Active Pass-through to Radio
        - You will see {"awk": "success"}
        - Enter IP address again
      - Click Choose file radio\_channel\_Champion
        - Then Upload radio channel list
        - You will see {"awk": "success"}
        - Enter IP address again
        - Click Inactivate Pass-through
        - You will see {"awk": "success"}
- Connect to GPS, Enter GPS IP address again, and go back to the firmware selection



- Config File
  - Click Browse and choose file Config-1.6.55\_20Hz
- Connect to GPS, Enter GPS IP address again, and go back to the firmware selection
  - Choose GNSS Board Upgrade
    - Click Browse and select file update\_gnss\_v5.42\_02\_b20190812
      - This will take about 20 minutes to complete.